

BT1000HD FOR REQUIRED EMERGENCY GENERATOR TESTING

BT1000HD is a professional battery & electrical system tester that features a 6/12V batteries / 24V pack test for emergency generators and provides complete test results within one single print out receipt.

BT1000HD FEATURES:

- Battery, Cranking, & Charging System Tester
- 24V Pack Test / 6V & 12V Battery Test
- 12V & 24V Cranking/Charging System Test / IR Test
- 4 Color LCD Screen Shows Different Colors for Various Test Results
- Built-in 2 1/4" Thermal Printer Prints Test Result With Date for Records
- Temperature Compensation for Above/Below 0°C (32°F)
- Customizable Facility Information on the Printout Test Result
- Detachable / Replaceable 10-foot Cable for Easy Replacement
- Heavy Duty Casing with Strong and Durable Case Design
- Test Code Decoder for Decoding and Saving Test Records
- Print Last Result Ability to Directly Print Last Test Result Without Re-testing
- 12-Month Warranty



BT1000HD Specifications:

Operating Range: CCA: 40-2000

Application: 24V Pack Test, 6V

& 12V Battery, 12V START-STOP Battery Test, 12V & 24V Cranking/Charging System Test, IR test

Voltage Range: 1V - 31.5V

Battery Types: Flooded, VRLA/GEL.

AGM Flat, AGM Spiral,

EFB

Battery Ratings: CCA/SAE, EN, JIS,

DIN, IEC, CA/MCA

0° C to 50° C Operating Temp:

(32° F to 122° F)